HARDIN MARINE

11 Industry Dr. Palm Coast, FL 32137 820-910030


TITLE:

BBC LOW MOUNT PORT ALTERNATOR BRACKET


www.hardin-marine.com

INSTALLATION INSTRUCTIONS:

- 1)MOUNT MAIN BRACKET, FIG. A, TO THE BLOCK USING #2 BOLT & #1 WASHER IN LOWER BOLT HOLE. DO NOT TORQUE.
- 2) INSTALL ALTERNATOR SWING ARM, FIG. B, INTO THE UPPER BOLT HOLE USING #3 BOLT & #1 WASHER. DO NOT TORQUE.
- 3) INSTALL THE 2" WIDE ALTERNATOR BOSS INTO THE LOWER PART OF THE MAIN BRACKET USING #9 BOLT, #7 & 8 WASHER. DO NOT TORQUE.
- 4) USING #6 BOLT, #4 & 5 WASHER, ATTACH ALTERNATOR TO THE SWING ARM.
- 5) INSTALL 33-1/2 LONG BELT, NOT SHOWN.
- 6) USING 5/8 SOCKET TORQUE 7/16 BOLTS TO 45 FT. LBS..
- 7) USING 9/16 SOCKET TORQUE 3/8 BOLT TO 35 FT. LBS..
- 8) USING 1/2 SOCKET TORQUE 5/16 BOLT TO 25 FT. LBS..



| ITEM NO. | PART NUMBER | DESCRIPTION | QTY. |
|----------|--------------|-------------------------|------|
| 1 | 90043AN-STSS | WASHER, 7/16AN | 2 |
| 2 | 90043C125HHS | BOLT, 7/16-14 x 1.25 | 1 |
| 3 | 90043C275HHS | BOLT, 7/16-14x2.75 | 1 |
| 4 | 90031SL-STSS | WASHER, 5/16 LOCK | 1 |
| 5 | 90031SA-STSS | WASHER, 5/16 SAE | 1 |
| 6 | 90031C125HHS | BOLT, 5/16-18x1.25 | 1 |
| 7 | 90037SL-STSS | WASHER, LOCKING - 3/8 | 1 |
| 8 | 90037SA-STSS | WASHER, 3/8 SAE | 1 |
| 9 | 90037C300HHS | BOLT, HHCS, 3/8-16x3.00 | 1 |
| | | | |



THIS DRAWING IS CONFIDENTIAL AND IS SUPPLIED ON EXPRESS CONDITION THAT IT SHALL NOT BE LENT, COPIED OR DISCLOSED TO ANY OTHER PERSON OR USED FOR ANY OTHER PURPOSE WITHOUT WRITTEN CONSENT OF HARDIN MARINE INC.. BREACH OF THIS CONTRACT WILL HOLD AND IT'S PRINCIPALS LIABLE FOR LOSS AND DAMAGES.